

BILL OF MATERIAL FOR COBRA 1000GTL

CIRCUIT SYMBOL	DESCRIPTION	DYNASCAN PART NO.
SEMICONDUCTORS		
IC-1	Integrated Circuit,	TA7222P, AF POWER 307-143-9-003
IC-2,3	Integrated Circuit,	TA7310P, VCO, TX MIX 307-133-9-004
IC-4	Integrated Circuit,	μPD2816C, PLL 307-145-9-001
IC-701	Integrated Circuit,	TM4801P, CLOCK 307-149-9-001
TR-4	Field Effect Transistor,	2SK104-H..... 182-055-9-001
TR-3,21	Field Effect Transistor,	2SK19-BL 182-037-9-001
TR-16,17,24,702,802	Transistor,	2SA733-P 177-020-9-001
TR-15	Transistor,	2SC458-C 176-048-9-002
TR-1,8,9,13,19,23,203,801,26	Transistor,	2SC945A-Q 176-062-9-001
TR-201	Transistor,	2SC1061-C 172-044-9-001
TR-18,202	Transistor,	2SC1096-3ZL 172-024-9-001
TR-2	Transistor,	2SC1674-L 176-081-9-002
TR-5,6,7,14,22,25	Transistor,	2SC1675-L 176-065-9-001
TR-11	Transistor,	2SC2028-B/20 172-038-9-001
TR-10	Transistor,	2SC2029-B/10..... 172-038-9-002
TR-12	Transistor,	2SC2076-C 176-060-9-004
D-6,7,11,12,16,28	Diode,	1N60-AM 150-014-9-001
D-9,10	Diode,	1N60-P 150-006-9-001
D-4	Diode,	1S34 150-016-9-001
D-5	Diode,	1S2075-K 151-028-9-001
D-1,2,3,15,17,19,20,24,27,801,802	Diode,	1S2076 153-008-9-001
D-201,202,203,204	Diode,	GM-3Y 151-079-9-001
D-13,26	Diode,	SR1K-1 151-040-9-003
D-205	Diode, Zener,	BZ-162 152-057-9-001
D-206	Diode, Zener,	WZ-071..... 152-075-9-001
D-21	Diode, Zener,	XZ-051 152-088-9-001
D-25	Diode, Zener,	XZ-086 152-089-9-001
D-701	Diode, Zener,	CZ-092 152-051-9-001
D-501	Diode, LED	TLR325, CH LED 158-023-9-001
D-702	Diode, LED	TLR2077, CLOCK LED 158-023-9-002
D-18	Diode, Varicap,	1S2687-D 153-008-9-001
D-14	Diode, Varicap,	1S2688-EA 154-004-9-001
INDUCTORS		
L-1	Coil,	LA-029 060-023-9-001
L-25	Coil,	LA-088 066-019-9-002
L-6	Coil,	LA-106 060-019-9-002
L-2	Coil,	LA-138 046-024-9-001
L-19	Coil,	LA-166 066-025-9-005
L-4	Coil,	LA-180 060-024-9-001
L-23	Coil,	LA-182 060-024-9-003
L-24	Coil,	LA-198 060-029-9-001
L-18	Coil,	LA-201 046-024-9-002
L-7	Coil,	LA-204 046-024-9-003
L-8	Coil,	LA-207 046-025-9-001
L-17	Coil,	LA-208 060-029-9-004
L-21	Coil,	LA-217 060-030-9-003

**CIRCUIT
SYMBOL**

DESCRIPTION

**DYNASCAN
PART NO.**

INDUCTORS (Continued)

L-5	Coil,	LA-274	046-025-9-002
L-20	Coil,	LA-275	046-025-9-003
L-3	Coil,	LA-277	046-025-9-004
L-10,16	Coil,	LC-018	041-056-9-003
L-13	Coil,	LC-019	041-088-9-001
L-14	Coil,	LD-012	041-069-9-004
L-12	Coil,	LE-088	041-104-9-001
L-11	Coil,	LE-089	041-104-9-002
L-9	Bead Core,	LD-071	044-043-9-006
L-15	Bead Core,	LD-087	044-048-9-003
L-301	Bead Core,	LD-088	044-051-9-001
L-26	Microinductor,	LZ-001, 10 μ H	041-105-9-001
L-22	Microinductor,	LZ-001, 100 μ H	041-062-9-002
T-301	Power Transformer,	TF-149	065-144-9-001
T-1	Output Transformer,	TF-129	061-039-9-001
T-2	Choke Coil,	TF-083	042-021-9-001

SEMI-FIXED & VARIABLE RESISTORS

VR-1	Resistor, Semifixed,	RV-189	300 ohm B.....	008-345-9-001
VR-201	Resistor, Semifixed,	RV-189	500 ohm B	008-342-9-001
VR-4	Resistor, Semifixed,	RV-189	20K ohm B	008-316-9-003
VR-6	Resistor, Semifixed,	RV-189	5K ohm B	008-316-9-004
VR-2	Resistor, Semifixed,	RV-189	30K ohm B	008-331-9-001
VR-5	Resistor, Semifixed,	RV-189	50K ohm B	008-316-9-002
VR-3	Resistor, Semifixed,	RV-189	100K ohm B	008-316-9-001
VR-301	Resistor, Variable,	1K ohm B, RV-287,	RF GAIN ...	008-350-9-001
VR-302	Resistor, Variable,	50K ohm A, RV-333,	TONE	008-347-9-004
VR-303	Resistor, Variable,	50K ohm A, RV-320,	VOL	008-347-9-002
VR-304	Resistor, Variable,	50K ohm B, RV-331,	SQ	008-347-9-003
VR-305	Resistor, Variable,	5K ohm B, RV-074,	SWR-CAL ..	008-350-9-002
VR-306	Resistor, Variable,	20K ohm B, RV-039,	DELTA-TUNE..	008-350-9-003
VR-307	Resistor, Variable,	5K ohm A, RV-293,	MIKE GAIN.....	008-344-9-005

FIXED RESISTORS

R-603,604	Resistor, Metal Film,	22 ohm	2W	\pm 10%	013-038-9-003
R-95	Resistor, Metal Film,	200 ohm	2W	\pm 10%	013-015-9-002
R-93	Resistor, Metal Film,	15 ohm	1W	\pm 10%	013-038-9-001
R-401,402,403	Resistor, Metal Film,	47 ohm	1W	\pm 10%	013-038-9-002
R-702,112	Resistor, Metal Film,	150 ohm	1W	\pm 10%	013-039-9-001
R-82	Resistor, Metal Film,	22 ohm	1/2W	\pm 10%	011-125-9-005
R-601,602	Resistor, Metal Film,	220 ohm	1/2W	\pm 10%	013-039-9-002
R-701	Resistor, Cement,	150 ohm	7W	\pm 5%	013-039-9-003
R-44	Resistor, Solid,	1K ohm	1/2W	\pm 10%	013-039-9-004
R-301	Resistor, Solid,	1.5M ohm	1/2W	\pm 10%	013-039-9-005
R-49	Resistor, Carbon Film,	4.7 ohm	1/2W	\pm 5%	002-102-5-479
R-201	Resistor, Carbon Film,	220 ohm	1/2W	\pm 5%	002-102-5-221
R-303	Resistor, Carbon Film,	2.2M ohm	1/2W	\pm 5%	002-102-5-225
R-110	Resistor, Carbon Film,	56 ohm	1/4W	\pm 5%	002-102-5-560
R-103	Resistor, Carbon Film,	2.2 ohm	1/8W	\pm 5%	002-108-5-229
R-50	Resistor, Carbon Film,	3.9 ohm	1/8W	\pm 5%	002-108-5-399
R-8,11,22,27,51	Resistor, Carbon Film,	100 ohm	1/8W	\pm 5%	002-108-5-101
R-24	Resistor, Carbon Film,	470 ohm	1/8W	\pm 5%	002-108-5-471

**CIRCUIT
SYMBOL**

DESCRIPTION

**DYNASCAN
PART NO.**

FIXED RESISTORS (Continued)

R-204	Resistor, Carbon Film, 680 ohm 1/8W	±5%	002-108-5-681
R-203,205	Resistor, Carbon Film, 820 ohm 1/8W	±5%	002-108-5-821
R-64,202	Resistor, Carbon Film, 1.2K ohm 1/8W	±5%	002-108-5-122
R-68	Resistor, Carbon Film, 2.2K ohm 1/8W	±5%	002-108-5-222
R-94,1	Resistor, Carbon Film, 2.7K ohm 1/8W	±5%	002-108-5-272
R-97	Resistor, Carbon Film, 3.3K ohm 1/8W	±5%	002-108-5-332
R-69,104	Resistor, Carbon Film, 4.7K ohm 1/8W	±5%	002-108-5-472
R-120	Resistor, Carbon Film, 6.8K ohm 1/8W	±5%	002-108-5-682
R-108	Resistor, Carbon Film, 5.6K ohm 1/8W	±5%	002-108-5-562
R-46,109,39	Resistor, Carbon Film, 10K ohm 1/8W	±5%	002-108-5-103
R-98,21	Resistor, Carbon Film, 22K ohm 1/8W	±5%	002-108-5-223
R-57	Resistor, Carbon Film, 100K ohm 1/8W	±5%	002-108-5-104
R-804	Resistor, Carbon Film, 68 ohm 1/4W	±5%	002-104-5-680
R-92	Resistor, Carbon Film, 470 ohm 1/4W	±5%	002-104-5-471
R-47	Resistor, Carbon Film, 1 ohm 1/8W	±5%	002-108-5-109
R-85,99	Resistor, Carbon Film, 10 ohm 1/8W	±5%	002-108-5-100
R-48,55	Resistor, Carbon Film, 22 ohm 1/8W	±5%	002-108-5-220
R-73	Resistor, Carbon Film, 33 ohm 1/8W	±5%	002-108-5-330
R-52	Resistor, Carbon Film, 47 ohm 1/8W	±5%	002-108-5-470
R-6,72,74	Resistor, Carbon Film, 56 ohm 1/8W	±5%	002-108-5-560
R-86	Resistor, Carbon Film, 82 ohm 1/4W	±5%	002-104-5-820
R-16,65,83,122,134	Resistor, Carbon Film, 100 ohm 1/8W	±5%	002-108-5-101
R-63	Resistor, Carbon Film, 180 ohm 1/8W	±5%	002-108-5-181
R-26	Resistor, Carbon Film, 220 ohm 1/8W	±5%	002-108-5-221
R-107	Resistor, Carbon Film, 470 ohm 1/8W	±5%	002-108-5-471
R-45	Resistor, Carbon Film, 560 ohm 1/8W	±5%	002-108-5-561
R-20,43,501,502,503, 504,505,506,507,508, 509,510,511,512,513, 514	Resistor, Carbon Film, 680 ohm 1/8W	±5%	002-108-5-681
R-42,59	Resistor, Carbon Film, 820 ohm 1/8W	±5%	002-108-5-821
R-17,19,96,100,105,132, 7,802	Resistor, Carbon Film, 1K ohm 1/8W	±5%	002-108-5-102
R-61	Resistor, Carbon Film, 1.5K ohm 1/8W	±5%	002-108-5-152
R-10,14,18,53	Resistor, Carbon Film, 2.2K ohm 1/8W	±5%	002-108-5-222
R-114,803	Resistor, Carbon Film, 1.2K ohm 1/8W	±5%	002-108-5-122
R-79,66	Resistor, Carbon Film, 1.8K ohm 1/8W	±5%	002-108-5-182
R-25,117	Resistor, Carbon Film, 3.3K ohm 1/8W	±5%	002-108-5-332
R-35	Resistor, Carbon Film, 3.9K ohm 1/8W	±5%	002-108-5-392
R-15,67,115,705,91	Resistor, Carbon Film, 4.7K ohm 1/8W	±5%	002-108-5-472
R-4,23,101	Resistor, Carbon Film, 5.6K ohm 1/8W	±5%	002-108-5-562
R-9,54,62,81	Resistor, Carbon Film, 6.8K ohm 1/8W	±5%	002-108-5-682
R-3,13,34,37,56,76,88,106, 121,124,126,70,119,706	Resistor, Carbon Film, 10K ohm 1/8W	±5%	002-108-5-103
R-133	Resistor, Carbon Film, 15K ohm 1/8W	±5%	002-108-5-153
R-32,33,71,77,5,75	Resistor, Carbon Film, 22K ohm 1/8W	±5%	002-108-5-223
R-2	Resistor, Carbon Film, 27K ohm 1/8W	±5%	002-108-5-273
R-80,84	Resistor, Carbon Film, 12K ohm 1/8W	±5%	002-108-5-123
R-36,40	Resistor, Carbon Film, 39K ohm 1/8W	±5%	002-108-5-393
R-38,128,60,102	Resistor, Carbon Film, 47K ohm 1/8W	±5%	002-108-5-473
R-28,31	Resistor, Carbon Film, 56K ohm 1/8W	±5%	002-108-5-563
R-29,30,78	Resistor, Carbon Film, 82K ohm 1/8W	±5%	002-108-5-823
R-127,129,180	Resistor, Carbon Film, 100K ohm 1/8W	±5%	002-108-5-104
R-801	Resistor, Carbon Film, 390K ohm 1/8W	±5%	002-108-5-394
R-123,704,41	Resistor, Carbon Film, 1M ohm 1/8W	±5%	002-108-5-105

**CIRCUIT
SYMBOL**

DESCRIPTION

**DYNASCAN
PART NO.**

FIXED RESISTORS (Continued)

R-125	Resistor, Carbon Film, 2.2M ohm 1/8W ±5%	002-108-5-225
R-118	Resistor, Carbon Film, 1.5M ohm 1/8W ±5%	002-108-5-155

CAPACITORS

C-128	Capacitor, Electrolytic, 0.47 μF 50V	022-157-9-001
C-29,59,,93,152	Capacitor, Electrolytic, 1 μF 50V	022-157-9-002
C-204	Capacitor, Electrolytic, 2200 μF 35V CZ-048	022-175-9-004
C-39,153	Capacitor, Electrolytic, 2.2 μF 25V	022-158-9-002
C-45,72	Capacitor, Electrolytic, 4.7 μF 25V	022-157-9-003
C-116	Capacitor, Electrolytic, 220 μF 25V	022-175-9-003
C-1,37,57,89,67,135	Capacitor, Electrolytic, 10 μF 16V	022-157-9-004
C-36	Capacitor, Electrolytic, 22 μF 16V	022-157-9-005
C-134	Capacitor, Electrolytic, 33 μF 16V	022-157-9-006
C-115,205	Capacitor, Electrolytic, 220 μF 16V	022-163-9-003
C-74	Capacitor, Electrolytic, 470 μF 16V	022-076-9-008
C-43	Capacitor, Electrolytic, 1000 μF 16V	022-158-9-004
C-73,120,126,150 154,804	Capacitor, Electrolytic, 47 μF 10V	022-160-9-002
C-114,801,121	Capacitor, Electrolytic, 100 μF 10V	022-157-9-008
C-112	Capacitor, Electrolytic, 470 μF 6.3V	022-158-9-008
C-91,92	Capacitor, Tantalum, 2.2 μF 16V ±20%	027-033-9-001
C-41	Capacitor, Tantalum, 4.7 μF 16V ±20%	027-026-9-004
C-25,70	Capacitor, Tantalum, 10 μF 10V ±20%	027-025-9-001
C-129	Capacitor, Aluminum, 0.1 μF 16V ±20%	022-177-9-001
C-22	Capacitor, Myler, 0.001 μF 25V ±20%	025-134-9-001
C-127,76,27	Capacitor, Myler, 0.0022 μF 25V ±20%	025-134-9-002
C-31	Capacitor, Myler, 0.0047 μF 25V ±20%	025-134-9-003
C-38	Capacitor, Myler, 0.0033 μF 25V ±20%	
C-32,33,40,44,124	Capacitor, Myler, 0.01 μF 25V ±20%	025-137-9-002
C-95,122	Capacitor, Myler, 0.022 μF 25V ±20%	025-137-9-006
C-18,19	Capacitor, Myler, 0.039 μF 25V ±20%	025-134-9-006
C-77	Capacitor, Ceramic Disc, 0.1 μF 25V ^{+80%} / _{-20%} BC..	020-210-9-008
C-20	Capacitor, Ceramic Disc, 1 pF 50V ±0.25pF SL..	020-190-9-001
C-51	Capacitor, Ceramic Disc, 2 pF 50V ±0.25pF SL..	020-187-9-001
C-80	Capacitor, Ceramic Disc, 8 pF 50V ±0.5pF SL..	020-213-9-001
C-98	Capacitor, Ceramic Disc, 15 pF 50V ±10% SL..	020-180-9-010
C-303,163,62	Capacitor, Ceramic Disc, 22 pF 50V ±10% SL..	020-180-9-011
C-99,100	Capacitor, Ceramic Disc, 39 pF 50V ±10% SL..	020-190-9-007
C-49	Capacitor, Ceramic Disc, 56 pF 50V ±10% SL..	
C-55,165,79	Capacitor, Ceramic Disc, 100 pF 50V ±10% SL..	020-180-9-016
C-166	Capacitor, Ceramic Disc, 150 pF 50V ±10% SL..	020-180-9-014
C-107,52,61	Capacitor, Ceramic Disc, 220 pF 50V ±10% SL..	020-180-9-019
C-84,53	Capacitor, Ceramic Disc, 330 pF 50V ±10% SL..	020-181-9-008
C-702	Capacitor, Ceramic Disc, 560 pF 50V ±10% SL..	020-213-9-003
C-167	Capacitor, Ceramic Disc, 680 pF 50V ±10% SL..	020-187-9-007
C-71,75,83,162,164,403, 404,405,406,601,602, 603,158,452,453,454, 304,305,401,402	Capacitor, Ceramic Disc, 0.001 μF 50V ^{+80%} / _{-20%} YF..	020-190-9-012
C-803	Capacitor, Ceramic Disc, 0.0033 μF 50V ^{+80%} / _{-20%} YF..	020-190-9-013
C-2,5,7,8,9,10,11,12,13,42, 58,64,66,69,78,81,82,85, 96,97,101,102,103,105, 110,117,118,125,130,133, 136,140,141,143,144,145, 159,160,161,168,169,201, 202,203,207,208,301,302	Capacitor, Ceramic Disc, 0.01 μF 50V ^{+80%} / _{-20%} YF..	020-190-9-015

CIRCUIT SYMBOL

DESCRIPTION

DYNASCAN PART NO.

CAPACITORS (Continued)

C-90	Capacitor, Ceramic Disc,	0.022 μ F	25V	+80% -20%	ZF..	020-213-9-004
C-16,17,21,23,24,26,35,46, 47,56,68,111,113,116,146, 147,206,701,802	Capacitor, Ceramic Disc,	0.039 μ F	25V	+80% -20%	ZF..	020-206-9-001
C-14	Capacitor, Ceramic Disc,	2 pF	50V	± 0.25 pF	CH	020-180-9-002
C-104,106	Capacitor, Ceramic Disc,	10 pF	50V	± 0.5 pF	CH	020-213-9-005
C-109	Capacitor, Ceramic Disc,	9 pF	50V	± 0.5 pF	RH	020-213-9-006
C-88	Capacitor, Ceramic Disc,	15 pF	50V	$\pm 10\%$	RH	020-207-9-006
C-4	Capacitor, Ceramic Disc,	22 pF	50V	$\pm 10\%$	RH	020-205-9-002
C-50	Capacitor, Ceramic Disc,	56 pF	50V	$\pm 10\%$	RH	020-208-9-002
C-86	Capacitor, Ceramic Disc,	68 pF	50V	$\pm 10\%$	RH	020-196-9-001
C-108	Capacitor, Ceramic Disc,	100 pF	50V	$\pm 10\%$	RH	020-204-9-010
C-87	Capacitor, Ceramic Disc,	150 pF	50V	$\pm 10\%$	RH	020-207-9-008
C-94	Capacitor, Ceramic Disc,	47 pF	50V	10%	UJ	020-207-9-002
C-451	Capacitor, Ceramic Disc,	0.001 μ F	50V	10%	YB	020-210-9-007
C-54	Capacitor, Ceramic Disc,	0.0047 μ F	50V	20%	YD	020-204-9-018
C-60,63,65,142	Capacitor, Ceramic Disc,	0.01 μ F	50V	20%	YD	020-204-9-019
CC-1	Capacitor, Array,	0.01 μ F x 4,	HA-003		527-077-9-002

CRYSTALS

X-1	Crystal,	QX-074,	10.240 MHz		132-027-9-001
XF-1	Crystal Filter,	FL-055,	10.695 MHz		143-011-9-001
CF-1	Ceramic Filter,	FL-009,	455 kHz		140-009-9-001

MISCELLANEOUS

	Printed Circuit Board,	PC-407 AB, Main			
	Printed Circuit Board,	PC-399AA, SP. JACK			
	Printed Circuit Board,	PC-408AA, MIKE JACK			
	Printed Circuit Board,	PC-410AB, DC POWER SUPPLY			
	Printed Circuit Board,	PC-301AA, SW			
	Printed Circuit Board,	PC-403AA, CH SW			
	Printed Circuit Board,	PC-367AA, CH LED			
	Printed Circuit Board,	PC-400AA, CLOCK			
	Printed Circuit Board,	PC-300AA, ALARM			
	Printed Circuit Board,	PC-311AA, PHONE			302-346-9-001
S-501	Switch, Rotary	SR-216	CH SW		083-243-9-001
S-701,702	Switch, Push, Dual	SW-158	ALARM/SET		088-047-9-001
S-703,704,705	Switch, Push, Triple	SW-159	FAST/SLOW/HOLD		088-047-9-002
S-304	Switch, Slide,	SW-099	AC-DC		084-065-9-003
S-308,302	Switch, Lever,	SW-151	SP1 - SP1 + 2 - SP2		080-010-9-001
			SWR - CAL - MOD		
S-301,303,306	Switch, Lever,	SW-152	ANL - PA - CB		080-010-9-002
			NB - OFF		
SP-301	Speaker,	SP-003			580-013-9-001
SP-801	Speaker,	SP-054	Clock Alarm		583-001-9-001
M-301	Meter,	MT-160	S/RF		320-100-9-001
M-302	Meter,	MT-161	MOD/SWR		320-100-9-002
	Microphone	MK-075			562-025-9-001

**CIRCUIT
SYMBOL**

DESCRIPTION

**DYNASCAN
PART NO.**

MISCELLANEOUS (Continued)

PL-301	Lamp	PL-065	S/RF	400-057-9-001
PL-302	Lamp	PL-065	MOD/SWR	400-058-9-001
PL-303	Lamp	PL-065	TX	400-057-9-002
PL-304	Lamp	PL-065	RX	400-058-9-002
J-301	Connector,	JK-035	ANT	772-027-9-001
J-302	Jack,	JK-052	DC PWR	762-020-9-001
J-303,401,402,403	Jack,	JK-001	REC/PA SP/EXT SP1/EXT SP2	773-077-9-001
J-451	Jack,	JK-058,	Mike	773-073-9-001
J-601	Jack,	JK-005,	PHONES	773-094-9-001
P-301	Plug,	PG-003,	SP BOX	775-034-9-001
TP-1,2,3,4,5,6	Terminal	TP-029,	Test Point	757-033-9-001
F-301,302	Fuse,	2A	250V, FS-012	191-251-3-002
	Fuse Hodler,	FH-002	742-035-9-001
	Insulator,	YD-039,	IC-1	342-046-9-002
	Insulator,	YD-033,	TR-201	345-050-9-002
	Insulator,	YD-043,	TR-11	342-047-9-001
	Insulator,	YD-042,	TR-10	342-047-9-002
	Clamper, Wire,	YY-047	380-278-9-001
	Clamper, Lead,	YY-049	380-284-9-002
FC-501	Flat Cable,	WF-114	426-046-9-001
FC-502	Flat Cable,	WF-116	426-046-9-002
FC-701,702	Flat Cable,	WF-115	426-046-9-003
	Chassis		
	Cover, Top		253-068-9-001
	Cover, Bottom		252-026-9-001
	Chassis, Front		254-032-9-001
	Panel, Side (R)		263-009-9-001
	Panel, Side (L)		263-009-9-002
	Panel, Rear		262-022-9-001
	Holder, Lamp		251-357-9-001
	Holder, Meter		251-357-9-002
	Holder, Switch		251-357-9-003
	Angle, Switch		251-227-9-001
	Heat Sink		747-052-9-002
	Heat Sink		747-065-9-001
	Holder, Integrated Circuit		762-021-9-001
	Holder, Transformer		251-173-9-003
	Lug Terminal		740-024-9-001
	Hanger, Microphone		741-074-9-001
	Cabinet, Wood		290-004-9-001
	Panel, Front		255-174-9-001
	Knob Channel		751-168-9-001
	Knob		751-168-9-004
	Knob, Push Switch		751-168-9-007
	Bushing, Phone Jack		763-114-9-001
	Control Nameplate		600-049-9-001
	Control Nameplate		600-049-9-002
	Brand Nameplate		600-049-9-003
	FCC Nameplate		
	Label, Fuse		
	Label, Caution		
	Label, Caution		483-337-9-002
	Label, Serial Number		

CIRCUIT
SYMBOL

DESCRIPTION

DYNASCAN
PART NO.

MISCELLANEOUS (Continued)

Label, Production Date.....		
Label, Warning		484-035-9-001
Display Plate, Clock/RX-TX		763-115-9-001
Optical Filter, LED CLOCK		763-115-9-002
Plate, Receive display.....		763-115-9-003
Plate, On the air display.....		763-115-9-004
Optical Filter, CH display		763-115-9-005
Protection Cover, Front Panel		502-113-9-001
Protection Cover, Front Panel		502-113-9-002
Cushion, Meter		502-113-9-003
Cushion, Meter		502-113-9-004
Washer, Rubber		347-075-9-001
Washer, Bakelite		347-080-9-001
Spacer, Alarm PCB		759-085-9-001
Screw, Bind Head 2.6 x 4 m/m		634-073-9-001
Screw, Bind Head 3 x 5 m/m		634-067-9-002
Screw, Bind Head 3 x 8 m/m		634-067-9-001
Screw, Bind Head 4 x 10 m/m		634-084-9-001
Screw, Bind Head 5 x 14 m/m		634-105-9-001
Screw, Flat Head 3 x 6 m/m		634-081-9-004
Screw, Round Head 3 x 6 m/m		634-105-9-002
Screw, Bind Head 3 x 8 m/m		710-032-9-002
Screw, Bind Head 3 x 6 m/m		710-021-9-004
Screw, Bind Head 3 x 14 m/m		710-032-9-001
Screw, Bind Head 3 x 16 m/m		710-043-9-001
Screw, Round Head 3.1 x 10 m/m		634-105-9-003
Screw, Pan Head 3 x 6 m/m		634-051-9-001
Nut, Flange 4 m/m		653-037-9-001
Washer, 3 m/m		724-021-9-001
Washer, 5 m/m		724-031-9-001
Foot, Rubber, 25 x 17 m/m		381-058-9-001
Spring, Channel Knob		763-084-9-004
Stopper, Cord		763-111-9-002
Rivet, FCC Nameplate		
Lug Terminal		
Accessory Box		500-382-9-001
Display Box		500-382-9-002
Shipping Box		
Protection Pad (R)		503-130-9-001
Protection Pad (L)		503-142-9-002
Protection Pad (C)		503-157-9-001
Protection Pad Paper		502-113-9-005
Instruction Manual		480-235-9-001
Circuit Diagram/Bill of Material		499-141-9-001
Warranty Card		
Service Station Card		
FCC Form 505		
FCC Form 555 B		
FCC Rule Part 95		
AC Cord, WZ-022		420-027-9-001
Cap Connector, YY-008		
DC Cord, W-070101, DC PWR.....		426-044-9-002
Clamper, Wire, YY-023		
Snap Bushing, YY-024		
Snap Bushing, YY-025		

499-141-9-001

CIRCUIT
SYMBOL

DESCRIPTION

DYNASCAN
PART NO.

SPEAKER BOX

Holder, Right Panel	251-357-9-004
Holder, Left Panel	251-357-9-005
Cover, Bottom.....	253-068-9-002
Panel, Rear	253-068-9-003
Plate, Baffle	260-165-9-001
Panel, Front	255-174-9-002
Speaker Grille (A).....	261-076-9-001
Speaker Grille (B).....	261-076-9-002
Cabinet, Wood	290-004-9-002
Plate (A)	260-165-9-002
Plate (B)	260-165-9-003
Plate (C)	260-165-9-004
Plate (D)	260-165-9-005
Cover, Cloth , Lever Switch	253-068-9-004