

K-PO DX-5000 Plus - Bandplan/frequency modification (should also work for non Plus version)

1. With the radio turned off, push and hold "FUNC" and "EMG" buttons while turning the radio on.
2. Select "1bAnd" or "2bAnd" with the channel selector.
3. Push and hold "FUNC" until the display first says "rES" and then "rEnd".
4. Release "FUNC" button, turn the radio off and then on again.

Done!